



Off.: F-34, Shopping Centre-1,
Mansarovar Garden,
New Delhi, India 110015

T: +91 11 2546 8263
F: +91 11 2546 2050

E: info@advancevibrators.com

W: www.advancevibrators.com

ADVANCE VIBRATORS

For High Frequency Shutter Vibrators 9000 VPM

Model No.	ADV-HFC-150-2	ADV-HFC-150-4	ADV-HFC-150-8	ADV-HFC-150-20
Input voltage (V)	415 V, 3 Phase AC	415 V, 3 Phase AC	415 V, 3 Phase AC	415 V, 3 Phase AC
Input supply frequency (Hz)	50 Hz	50 Hz	50 Hz	50 Hz
Output voltage (V)	48-55 V, 3 Phase AC	48-55 V, 3 Phase AC	48-55 V, 3 Phase AC	48-55 V, 3 Phase AC
Output supply frequency (Hz)	150 Hz	150 Hz	150 HZ	150 HZ
No. of vibrators that can be operated simultaneously.	2	4	8	20

For High Frequency Shutter Vibrators 6000 VPM and Motor-in-Head Immersion vibrators (40 mm, 57 mm, 65 mm, and 75 mm needle dia.)

Model No.	ADV-HFC-200-2	ADV-HFC-200-4	ADV-HFC-200-8	ADV-HFC-200-20
Input voltage (V)	415 V, 3 Phase AC	415 V, 3 Phase AC	415 V, 3 Phase AC	415 V, 3 Phase AC
Input supply frequency (Hz)	50 Hz	50 Hz	50 Hz	50 Hz
Output voltage (V)	48-55 V, 3 Phase AC	48-55 V, 3 Phase AC	48-55 V, 3 Phase AC	48-55 V, 3 Phase AC
Output supply frequency (Hz)	200 Hz	200 Hz	200 HZ	200 HZ
No. of vibrators that can be operated simultaneously .	2	4	8	20

For High Speed Dam Vibrators

Model No.	ADV-HFC-250-2	ADV-HFC-250-4	ADV-HFC-250-8
Input voltage (V)	415 V, 3 Phase AC	415 V, 3 Phase AC	415 V, 3 Phase AC
Input supply frequency (Hz)	50 Hz	50 Hz	50 Hz
Output voltage (V)	48-55 V, 3 Phase AC	48-55 V, 3 Phase AC	48-55 V, 3 Phase AC
Output supply frequency (Hz)	250 Hz	250 Hz	250 HZ
No. of vibrators that can be operated simultaneously .	2	4	8



Electronic Frequency Converter