



Off.: F-34, Shopping Centre-1,
Mansarovar Garden,
New Delhi, India 110015

T: +91 11 2546 8263
F: +91 11 2546 2050

ADVANCE VIBRATORS

E: info@advancevibrators.com

W: www.advancevibrators.com

External Vibrators for compacting, conveying, sieving, formwork, shuttering, sleeper plants, precast factories, pole factories etc.

ADVANCE High Frequency External Vibrators 9000 VPM

- They are operated through high frequency converters.

Technical Specifications

Model no.	ADV-S150-100	ADV-S150-150	ADV-S150-200
Capacity (kW)	1 kW	1.5 kW	2 kW
Input voltage (V)	48-55 V, 3 Phase AC	48-55 V, 3 Phase AC	48-55 V, 3 Phase AC
Supply Frequency (Hz)	150 Hz	150 Hz	150 Hz
Vibrations (VPM)	9000 VPM	9000 VPM	9000 VPM

- *Adjustable VPM upto 9000VPM also available on the above specifications*
- *Quick fixing and releasing system for vibrators (Cradle connection) available on request.*

ADVANCE High Frequency External Vibrators 6000 VPM

- They are operated through high frequency converters.

Technical Specifications

Model no.	ADV-S200-100	ADV-S200-150	ADV-S200-200
Capacity (kW)	1 kW	1.5 kW	2 kW
Input voltage (V)	48-55 V, 3 Phase AC	48-55 V, 3 Phase AC	48-55 V, 3 Phase AC
Supply Frequency (Hz)	200 Hz	200 Hz	200 Hz
Vibrations (VPM)	6000 VPM	6000 VPM	6000 VPM

- *Adjustable VPM upto 6000VPM also available on the above specifications*
- *Quick fixing and releasing system for vibrators (Cradle connection) available on request.*

ADVANCE High Frequency External Vibrators 3000 VPM

- They are operated directly through 415 volts, 3 phase AC power supply.

Technical Specifications

Model no.	ADV-S50HV-15	ADV-S50HV-30	ADV-S50HV-75	ADV-S50HV-150
Capacity (HP)	0.25 HP	0.5 HP	1 HP	2 HP
Input voltage (V)	415 volts, 3 Phase AC	415 volts, 3 Phase AC	415 volts, 3 Phase AC	415 volts, 3 Phase AC
Supply Frequency (Hz)	50 Hz	50 Hz	50 Hz	50 Hz
Vibrations (VPM)	3000 VPM	3000 VPM	3000 VPM	3000 VPM



Off.: F-34, Shopping Centre-1,
Mansarovar Garden,
New Delhi, India 110015

T: +91 11 2546 8263
F: +91 11 2546 2050

ADVANCE VIBRATORS

E: info@advancevibrators.com

W: www.advancevibrators.com

ADVANCE High Frequency Converter for 9000 VPM External Vibrators

Model No.	ADV-HFC-150-2	ADV-HFC-150-4	ADV-HFC-150-8
Input voltage (V)	415 V, 3 Phase AC	415 V, 3 Phase AC	415 V, 3 Phase AC
Input supply frequency (Hz)	50 Hz	50 Hz	50 Hz
Output voltage (V)	48-55 V, 3 Phase AC	48-55 V, 3 Phase AC	48-55 V, 3 Phase AC
Output supply frequency (Hz)	150 Hz	150 Hz	150 HZ
No. of vibrators that can be operated simultaneously.	2	4	8

ADVANCE High Frequency Converter for 6000 VPM External Vibrators

Model No.	ADV-HFC-200-2	ADV-HFC-200-4	ADV-HFC-200-8
Input voltage (V)	415 V, 3 Phase AC	415 V, 3 Phase AC	415 V, 3 Phase AC
Input supply frequency (Hz)	50 Hz	50 Hz	50 Hz
Output voltage (V)	48-55 V, 3 Phase AC	48-55 V, 3 Phase AC	48-55 V, 3 Phase AC
Output supply frequency (Hz)	200 Hz	200 Hz	200 HZ
No. of vibrators that can be operated simultaneously .	2	4	8

Note: Customized versions possible.



Industrial Vibrators



Concrete Shutter Vibrators